



ORDERING INFORMATION

Model	Description
CFC-30TM	100Base-TX to 100Base-FX Fiber Converter, ST Type/Multi-Mode/2KM

CFC-30TM–100BASE-TX TO 100BASE-FX FIBER CONVERTER, ST TYPE/MULTI-MODE/2KM

Using CFC-30TM is the simplest way to interconnect any equipment’s 100BASE-TX port to the 100BASE-FX interface network. It smoothly transfers data between RJ-45 port and 100BASE-FX Multi-Mode ST type Fiber port. Such a hybrid-networking device is based on the Transceiver in the IEEE 802.3u standards. CNet provides the most reliable quality and reasonable price to serve our customers.

CNet also provides a family of wired and wireless LAN products that deliver the same level of security, scalability, and manageability for WLANs that customers have come to expect in their wired LAN, including Routers, Switches, Modems, and Network adapters.

KEY FEATURES

- Supports Fast Ethernet 100Base-TX and 100Base-FX
- Operates at Maximum Packet Filtering and Forwarding Rate
- TP Port:100Mbps Full-/Half-duplex
- Fiber Port: 100Mbps Full-/Half-duplex

SPECIFICATIONS

Product Name	100Base-TX to 100Base-FX Fiber Converter, ST Type/Multi-Mode/2KM
Model Name	CFC-30TM
Fiber Mode	Multi-Mode
Wave Length	1310nm
Fiber Cable	62.5/125 μ m
Fiber Cable Distance	2KM
Fiber Connector	ST Type
TP Port	RJ-45 phone-type
LED Indicators	FX,TP:TX FX,TP:LINK FDX PWR
Power Adapter	External DC5V, 1A
Environment	Operating Temperature: -20° ~ 70° C (-4° ~ 158° F) Storage Temperature: -40° ~ 80° C (-40° ~ 176° F) Humidity: 10% ~ 90% Non-condensing
Certifications	CE, FCC
Dimensions	94 x 70.3 x 26.2 mm (3.7 x 2.77 x 1.03 inches)